VOTING BLOCK FOR IDENTIFYING WLAN SIGNAL MODULATION TYPE
Paul J. Husted

BACKGROUND OF THE INVENTION

Field of the Invention

[0001]   The present invention relates to a wireless local area network (WLAN) device that can receive signals of multiple modulation types. In particular, the present invention relates to a voting block that quickly and accurately identifies the modulation type of the signal.

Description of the Related Art

[0002]   Wireless local area networks (WLANs) are becoming increasingly popular as communication networks. The IEEE 802.11 standards provide guidelines for the operation of devices operating in WLANs. Specifically, the 802.11a standard defines communication in the 5 GHz band using data rates of 6, 12, 18, 24, 36, and 54 Mbps. The 802.11b standard defines communication in the 2.4 GHz band using data rates of 1, 2, 5.5, and 11 Mbps. A recently ratified addition to the 802.11 standards, called the 802.11g standard, uses the high data rates of 802.11a in the frequency band of 802.11b, i.e. 2.4 GHz.

[0003]   The 802.11g standard envisions that 802.11b devices can communicate with 802.11g devices that operate in the same WLAN. Note that as used herein, the term "device" can refer to either an access point or a client.

[0004]   To ensure backwards compatibility with 802.11b devices while allowing data rate increases, the 802.11g standard incorporates the modulation schemes from both the 802.11a and 802.11b standards. In general, modulation refers to the addition of information to a carrier.

Typical modulation techniques include frequency modulation wherein the frequency of the carrier waveform is varied.

[0005]   The 802.11b standard uses a modulation scheme called complementary code keying (CCK) (note that 802.11b can also use Barker code chipping at the 1 and 2 Mbps rates) whereas the 802.11a standard uses another modulation scheme called orthogonal frequency division multiplexing (OFDM). The OFDM scheme involves encoding information upon a plurality of sub-carriers, which are then modulated onto a carrier signal. The proposed 802.11g standard can use other modulation schemes in addition to CCK and OFDM. For example, a modified OFDM scheme called Extended Range (XR), which has been developed by Atheros Communications, Inc. to operate concurrently with the 802.11a, 802.11b, and 802.11g standards, can also be used.

[0006]   Of importance, the 802.11g standard provides no implementation requirements as to how a modulation type should be identified. Therefore, a need arises for a technique that quickly and accurately identifies signals of different modulations when received by the WLAN device.

SUMMARY OF THE INVENTION

[0007]   A wireless local area network (WLAN) device operating in an 802.11g mode can receive signals of different modulations. These modulations can include, for example, OFDM, CCK, or proprietary modulation schemes. To efficiently decode these signals while conserving valuable power resources in the device, it would be highly desirable to know what modulation is being used as soon as possible. Therefore, a technique is provided that quickly and accurately identifies signals of different modulations when received by the WLAN device.

[0008]   In accordance with one feature of the invention,
a method of determining a modulation type of a received
signal can include beginning demodulation of the received
signal using components associated with one or more
potential types of modulation. Identification values can
be provided to a voting block for potential types of
modulation based on the received signal. The voting block
can advantageously determine the most probable modulation
based on such identification values, thereby allowing the
system to use the correct decoder to decode the received
signal. The output of the voting block can be
advantageously used for deactivating components in the
device not associated with the identified modulation.

[0009]   The identification value can include a
correlation value based on characteristics of the type of
modulation. Specifically, each type of modulation has
inherent characteristics that can be used when searching
for a packet. The inherent characteristics could be found
by a self-correlating technique (e.g. identifying unique
signal patterns provided within the packet corresponding to
a particular type of modulation), a cross-correlating
technique (e.g. comparing signals in a packet to a known
pattern identified for a type of modulation), or a
combination of self- and cross-correlating (dual
correlating) techniques.

[0010]   The identification value for a weak signal can
include a normalized correlation value based on
characteristics of the type of modulation normalized by the
raw power in the signal. The identification value for a
strong or intermediate strength signal can include an
absolute modulation-specific correlation value, also called
a modulation-specific received signal strength indicator

(RSSI) herein. An RSSI can be computed by performing a
noise floor measurement and then subtracting the measured
noise floor power from the measured received signal power,
wherein all values are on a decibel (dB) scale. The
received signal power can be defined as the variable gain
subtracted from the sum of squares power after filtering
(i.e. fir_pwr – variable gain). Thus, an RSSI can be
represented by the following equation: (fir_pwr – variable
gain) - noise floor. Note that these measurements include
values that have been converted to the log domain (e.g. via
look-up tables).

[0011]   In one embodiment, for a strong or intermediate
strength signal, the identification value can include a
bias value, wherein the bias value adjusts a probability of
choosing a particular modulation. The bias value can be
based on an environment for the received signal, e.g
multipath, which can affect modulated signals in different
ways.

[0012]   In one embodiment, to determine whether a signal
is truly weak or is of intermediate strength, a raw RSSI
can be compared to a threshold RSSI. The raw RSSI refers
to the strength of the signal without reference to a
particular modulation. In one embodiment, the threshold
RSSI could be set by a user of the WLAN device.

[0013]   A system for determining a modulation of a
received signal in a receiver is also provided. The system
can include means for providing identification values for
potential types of modulation based on the received signal.
The system can further include means for determining the
most probable modulation based on such identification
values.

[0014]   In one embodiment including an appropriately fast microprocessor, a computer software program for determining the modulation type of a received signal can also be provided. The program can include code for providing identification values for potential types of modulation based on the received signal. The program can further include code for determining the most probable modulation based on such identification values.

BRIEF DESCRIPTION OF THE FIGURES

[0015]   Figure 1A illustrates a simplified receiver of a WLAN device, wherein a processing block therein can facilitate identifying the modulations of detected signals.

[0016]   Figure 1B illustrates a more detailed block diagram of a processing block, which includes a voting block. The voting block can identify the modulation type based on pattern characteristics and modulation-specific received signal strength indicators (RSSIs) associated with the detected signals.

[0017]   Figures 1C and 1D illustrate embodiments of receiver configurations in which a voting block can control various components, including decoder blocks, in the receiver.

[0018]   Figure 2A illustrates an exemplary OFDM modulated signal.

[0019]   Figure 2B illustrates an exemplary CCK modulated signal.

[0020]   Figure 3 illustrates an exemplary process that includes a search mode in which the variable gain of amplifiers in the receiver can be adjusted and a demodulation mode in which the modulation type of each packet can be identified.

[0021]   Figures 4A and 4B illustrate an exemplary
technique that can be used in a WLAN receiver to identify
the modulation of a received packet. This technique can
include computing a raw RSSI as well as modulation-specific
RSSIs.

DETAILED DESCRIPTION OF THE FIGURES

WLAN Receiver: Overview

[0022]   Figure 1A illustrates a simplified receiver 100
for receiving signals in a WLAN environment. In receiver
100, a bandpass filter 102 receives the incoming signals
from an antenna 101 and outputs a predetermined band of
frequencies (while excluding those frequencies higher and
lower than the predetermined band). A variable RF
amplifier 103 can provide an initial amplification to that
predetermined band of frequencies. A mixer 104 converts
those amplified signals into intermediate frequency (IF)
signals, which are then amplified by an IF amplifier 105.

[0023]   At this point, mixers 106 and low pass filters
107 (including both I and Q branches) can generate signals
in the desired channel (called the baseband signals).
Amplifiers 108 then amplify these baseband signals. Analog
to digital converters (ADCs) 110 (provided for both the I
and Q branches of low pass filters 107) transform the
amplified baseband signals into digital signals that can be
analyzed by a processing block 111. Gain control circuit
112 detects the magnitude of the digital signal, as
measured by processing block 111, and uses the detected
magnitude to adjust the gains of RF amplifier 103, IF
amplifier 105, and BB amplifiers 108.

[0024]   Of importance, processing block 111 determines
the modulation type of the detected signal and provides

this determination to both an OFDM/XR decoder 113 and a CCK decoder 114 for system optimization, thereby allowing the correct decoder to recover the originally transmitted signal. Moreover, after the modulation type of the signal is determined, various components of processing block 111 as well as one of OFDM/XR decoder 113 and CCK decoder 114 can be turned off, thereby decreasing use of expensive energy resources in the system.

[0025]   OFDM/XR decoder 113 and CCK decoder 114 can be implemented using conventional decoders. A generic conventional decoder could include a synchronizing block for time and frequency. In one embodiment, the synchronizing block could include a rotator for receiving the output of processing block 111 and providing a frequency offset correction to the processed signal, if necessary. The synchronizing block could further include a signal timing circuit for determining symbol boundaries and providing a timing output. The method for determining the frequency offset and timing values may be different for each modulation type, and the internal method of describing these values may be different as well. However, the general principal of finding timing alignment and correcting frequency offset still apply. The method for correcting these offsets may be shared or not between implementations if possible, but is not necessary. The timing output can be used by other components. For example, the timing output could be provided to a maximum-likelihood estimator and a Barker correlator in a CCK decoder or to an FFT, frequency equalizer, and a Viterbi decoder in an OFDM decoder.

Detection Of Weak Versus Strong Signals

[0026]   Gain control 112 attempts to adjust the gain of amplifiers 103, 105, and 108 so that the size of the received signal at ADCs 110 is neither too small nor too large, either of which can undesirably result in unreliable identification of the signal. Generally, high and low thresholds can be established, wherein if a detected signal fails to fall within the two thresholds, then the gain of these variable amplifiers can be adjusted to bring that signal back into the desired range. In one embodiment, amplifiers 103, 105, and 108 can be adaptively set to a relatively high gain to ensure that even thermal noise at antenna 101 can be detected at ADCs 110.

[0027]   In this state, if a weak signal is received, then the amplified signal at ADCs 110 is not substantially greater than the amplified thermal noise from antenna 101. In one embodiment, a power measurement block in processing block 111 (described in reference to Figure 1B) can determine whether the received signal may be characterized as weak, strong, or intermediate (i.e. somewhere between the two extremes). This power measurement block can then provide its output to gain control 112 to ensure proper adjustment of the gains of variable amplifiers 103, 105, and 108.

[0028]   In one embodiment, a first, coarse gain adjustment can be made based on the signal as received by processing block 111. If the subsequent signal does not fall within the established low and high thresholds, then additional coarse gain adjustments can be performed. These adjustments can continue until either the signal is within the established low and high thresholds or until the gain cannot change any further. At this point, fine gain.

adjustments can be made based on measurements taken after processing within processing block 111.

[0029]   After fine gain adjustments have been made, the search mode is complete and signal identification (also called the demodulation mode) can begin. In accordance with one feature of the invention, described in reference to Figures 4A and 4B, processing block 111 can identify the modulation type of the signal using a normalized correlation value or an absolute modulation-specific correlation value of the detected signal.

Processing Block Includes Packet Detection And Voting Capability

[0030]   Figure 1B illustrates processing block 111 in greater detail. For context, ADCs 110, gain control 112, CCK decoder block 114, and OFDM/XR decoder block 113 are shown. As shown in Figure 1B, ADCs 110 can directly provide an output to a power measurement block 140. In this configuration, power measurement block 140 can determine the magnitude of the detected signal as received by processing block 111. Gain control 112 can use this magnitude to provide coarse adjustments to the gains of the variable amplifiers discussed in reference to Figure 1A. In one embodiment, coarse gain adjustments are made until the signal is brought within the established high and low thresholds.

[0031]   As described above, the variable amplifiers can be set to a relatively high gain to ensure that in the absence of in-band signals even thermal noise at the antenna can be detected. Thus, in this case, gain control circuit 112 would typically perform coarse gain adjustments based on strong, not weak, signals. Fine gain adjustments

can be performed based on the output of an RRC FIR filter
120 and a FIR2 filter 126 (described in further detail
below) to optimize the signal size.

[0032]   Because the type of modulation of the packet is
initially unknown in the 802.11g mode, processing block 111
advantageously allows parallel demodulation of a packet,
thereby ensuring the quickest decoding time possible. To
provide this parallel demodulation, processing block 111
can provide the output of ADCs 110 to both CCK decoder
block 114 and OFDM/XR decoder block 113 via various
processing components.

[0033]   For example, in the case of CCK decoder block
114, RRC FIR filter 120 receives the output of ADCs 110.
RRC FIR filter 120 can be used when the sampling rate is
identified to be 44 MHz, and the desired data rate is 22
MHz. In other words, RRC filter 120 can be used to provide
a down sample of 2 to the output of ADCs 110 as well as to
provide matched filter pulse shaping and rejection of out-
of-band interference for optimal SNR. After this
processing, RRC filter 120 provides the 22 MHz signal to
CCK decoder block 121.

[0034]   In the case of OFDM/XR decoder block 113, a Turbo
line 122, a finite impulse response (FIR1) filter 123, and
an interpolator 124 all receive the output of ADCs 110 and
can provide various levels of OFDM/XR processing to the
detected signal. A multiplexer 125, which receives inputs
from Turbo line 122, FIR1 filter 123, and interpolator 124,
provides its single output to OFDM/XR decoder block 113.

[0035]   In one embodiment, turbo line 122 can be selected
when the sampling rate desired is 80 MHz (i.e. twice as
fast as a standard 802.11a signal). In one embodiment,
multiplexer 125 selects turbo line 122 only when receiver

100 is in the turbo mode, as determined by a value stored
in a turbo mode register 131. In accordance with one
feature of the invention, turbo line 122 can have a dual
use in receiver 100. Specifically, turbo line 122 can also
be selected when the received and desired data rate is 44
MHz. When receiver 100 is in the 802.11g mode, as
determined by a value in a dynamic mode register 152,
multiplexer 125 selects between turbo line 122 and
interpolator 124.

[0036]   Interpolator 124 can be selected when the
received data rate is 44 MHz, and the desired data rate is
40 MHz. Interpolator 124 can be implemented using
sequencing interpolator configurations described in U.S.
Patent Application Serial No. 10/367,527, entitled
"RECEIVING AND TRANSMITTING SIGNALS HAVING MULTIPLE
MODULATION TYPES USING SEQUENCING INTERPOLATOR", filed on
February 14, 2003 by Atheros Communications, Inc., and
incorporated by reference herein.

[0037]   Note that FIR1 filter 123 can be selected when
the received data rate is 80 MHz, and the desired data rate
is 40 MHz. In other words, FIR1 filter 123 can also be
used to provide a down sample of 2 to the output of ADCs
110. This data rate is used for receivers in the 802.11a
mode. Thus, in this embodiment, receiver 100 can conform
to both 802.11a and 802.11g standards.

[0038]   In this embodiment of receiver 100, RRC FIR
filter 120 and a FIR2 filter 126 (which is coupled to the
output of multiplexer 125) provide outputs to power
measurement block 140. In this configuration, power
measurement block 140 can provide further signal power
information to gain control 112, thereby allowing gain

control 112 to make additional fine gain adjustments to optimize signal size, if necessary.

[0039]   FIR2 filter 126 and a FIR2 filter 150 (which is substantially identical to FIR2 filter 126 but receives an output of interpolator 124) can be used to filter out any nearby blocking signals and reject any out-of-band interference for optimal SNR. A multiplexer 151 can selectively provide one of the outputs of FIR2 filter 126 and FIR2 filter 150 to an XR identifier 129. FIR2 filter 126 provides its output to an OFDM identifier 127. RRC FIR filter 120 provides its output to a CCK identifier 128.

[0040]   In general, identifiers 127, 128, and 129 can provide values to a packet detection block 160 during the search mode and to a voting block 130 during the demodulation mode. Specifically, and described in further detail below, identifiers 127, 128, and 129 can compute normalized power values in the search mode and absolute power modulation-specific RSSI values in the demodulation mode. Of importance, these values are computed based on certain characteristics. Note that the term "characteristic" can refer to any number of identifying means including, for example, patterns and/or periodicity of a given signal.

Characteristics Of Modulation Types

[0041]   Exemplary characteristics of each modulation type will now be discussed. For example, in an OFDM preamble shown in Figure 2A, twelve tones (complex sinusoidals) are spaced (peak to peak) at 1.25 MHz with a period of 0.8 µs. (Note that self-correlation at 44 MHz sampling rate (if interpolator 146 is not used) will require 35 samples,

compared to 32 samples at 40 MHz typically used in 802.11a. Advantageously, 35 samples at a 44 MHz sampling rate spans a period of 795 ns, which has virtually no degradation in performance from an ideal 800 ns self-correlation.

[0042]   Each of ten short training symbols t1-t10 in the OFDM preamble has these twelve sub-carriers, thereby establishing an OFDM pattern. Therefore, the output will be fully periodic, even in multipath. Thus, looking for periodicity of 0.8 µs is very effective to find the preamble, even in conditions of low signal to noise ratio (SNR) and heavy multipath. Hence, the term "self-correlation" is appropriate in describing OFDM detection.

[0043]   In contrast, in a CCK preamble (i.e. a SYNC signal) shown in Figure 2B, Barker signals (an 11-chip spreading code) are multiplied by either -1 or +1. Note that Figure 2B illustrates a short CCK format, in contrast to a long CCK format (as defined by the 2001 draft supplement to the IEEE 802.11b standard). However, the -1/+1 multiplication is applied in a similar manner, thereby establishing a CCK pattern. Hence, the term "cross-correlation" is appropriate in describing CCK detection.

[0044]   In an XR preamble, 15 symbols (called medium sequences) of duration 1.6 µs at the base rate (32 samples at Nyquist rate) are provided. These medium sequences are combined with a secondary PN codes, such that each medium has a predetermined sign (i.e. +/-). Preamble detection operates by cross-correlating the input signal with a single medium sequence, then self-correlating this output over a gap of the duration of a medium sequence. Therefore, an XR signal can have both self- and cross-correlation characteristics.

Operation Modes: Search And Demodulation

[0045]   Figure 3 illustrates a simplified flow chart of the principal operation modes for processing block 111. In a first operation mode, i.e. a search mode 310, a packet is detected in step 301. In processing block 111 (see Figure 1B), power measurement block 140 can provide this detection function after receiving the output of ADCs 110. After initial detection, the gain of the variable amplifiers can be adjusted in step 302. Note that this adjustment can include both coarse as well as fine gain adjustment. Gain control 112 can provide such adjustments after receiving one or more inputs from power measurement block 140. When the optimal signal gain is achieved, an appropriate signal is provided to various components of processing block 111. In one embodiment, the signal can be implemented as an agc_done signal (representing an end to automatic gain control). In processing block 111, packet detection block 160 can generate this agc_done signal.

[0046]   Note that a WLAN receiver conforming to the 802.11g standard (without XR activation) will only receive a 44 MHz signal. Therefore, in search mode 310, turbo line 122 can be selected to transfer its signal to OFDM/XR decoder block 113 and OFDM identifier 127 (via FIR2 filter 126).

[0047]   In a second operation mode, i.e. a demodulation mode 320, demodulation of the detected packet can begin in step 321. In accordance with one feature of the invention, this demodulation can be done with one or more decoder blocks. For example, in one embodiment of processing block 111, both CCK decoder block 114 as well as OFDM/XR decoder block 113 can initially operate in parallel. In step 322,

the modulation type of the packet can be determined. In
processing block 111, voting block 130 can perform this
function during the preamble of the packet. After the
determination of the modulation type, various components in
processing block 111 can be deactivated in step 323. In
one embodiment, voting block 130 can trigger this
deactivation functionality.

[0048]   For example, referring to Figure 1C, if an OFDM
or XR signal is identified, then any components associated
with CCK signals can be deactivated. In processing block
111, these components can include CCK decoder block 114 and
RRC FIR filter 120. In one embodiment, voting block 130
can deactivate a gated clock tree, which can deactivate CCK
decoder block 114 and RRC FIR filter 120 in parallel. In
other embodiments, CCK decoder block 114 and RRC FIR filter
120 can be deactivated in series.

[0049]   Similarly, referring to Figure 1D, if a CCK
signal is identified, then any components associated with
OFDM/XR signals can be deactivated. In processing block
111, these components can include OFDM/XR decoder block
113, FIR1 filter 123, interpolator 124, FIR2 filter 126,
FIR2 filter 150, multiplexer 125, and multiplexer 151. In
one embodiment, voting block 130 can deactivate OFDM/XR
decoder block 113, FIR1 filter 123, interpolator 124, FIR2
filter 126, FIR2 filter 150, multiplexer 125, and
multiplexer 151 in parallel. In other embodiments, OFDM/XR
decoder block 113, FIR1 filter 123, interpolator 124, FIR2
filter 126, FIR2 filter 150, multiplexer 125, and
multiplexer 151 can be deactivated in series.

[0050]   Moreover, referring back to Figure 1B, if XR
modulated signals will not be received, then interpolator
124, FIR2 filter 150, and multiplexer 151 can all be

15

powered down while still providing a low pass filtering for
incoming OFDM signals using turbo line 122 and FIR2 filter
126. If XR modulated signals can be received, then
interpolator 124 can be activated. In this case, FIR2
filter 126 will be receiving a 44 MHz signal and FIR2
filter 150 will be receiving a 40 MHz signal.

Packet Detection In Search Mode

[0051]   As described above, in one embodiment of search
mode 310, power management block 140 can detect the signal
strength of the received signal and provide the appropriate
output to gain control 112. The signal strength can be
characterized as weak or strong. For example, if the
received signal is equal to or less than a predetermined
threshold, then the received signal can be characterized as
weak. If the received signal is greater than this
predetermined threshold, then the received signal can be
characterized as strong.

[0052]   In another embodiment, different detection
mechanisms can be used to detect weak and strong signals.
Because it is unknown whether the next packet will be
strong or weak, these detection mechanisms can operate in
parallel. In one embodiment of the invention, the
detection mechanism for a weak signal can include outputs
from a cross-correlator, a self-correlator, and a dual
correlator. For example, CCK identifier 128, OFDM
identifier 127, and XR identifier 129 can implement the
detection mechanism for a weak signal and provide their
outputs to packet detection block 160. In contrast, the
detection mechanism for a strong signal can include an
indication of a jump in raw received signal strength
indicator (RSSI). In one embodiment, power measurement

block 140 can detect this jump and provide that

determination to packet detection block 160.

[0053]   In one embodiment of weak signal detection, a

cross-correlation technique for CCK identifier 128 can

compare known modulation patterns found in the preamble of

the signal with the detected signal. The power of this

correlation value can be normalized by the power in the sum

of the squares of the samples correlated upon. CCK

identifier 128 can provide this normalized value to packet

detection block 160, which can then compare this normalized

value to a predetermined threshold for CCK modulation (e.g.

0.5). If this normalized correlation exceeds a

predetermined threshold, then one or more gain adjustments

(i.e. fine gain adjustments) can be performed on the

variable amplifiers based on outputs from packet detection

block 160 to gain control 112.

[0054]   A substantially similar procedure could be

performed using a self-correlation technique for OFDM

identifier 127. In this case, each sample can be

multiplied by the conjugate of a sample a fixed number of

samples ago and summed for a fixed amount of time. The

power of this value can be normalized by the power of the

samples used in the self-correction and then compared to

another predetermined threshold for OFDM modulation (e.g.

0.45). If this normalized correlation exceeds the

predetermined threshold, then one or more gain adjustments

(i.e. fine gain adjustments) can be performed on the

variable amplifiers.

[0055]   U.S. Patent Application Serial No. 10/XXX,XXX,

entitled "Packet Detection Synchronization, And Frequency

Offset Estimation", U.S. Patent Application Serial No.

10/XXX,XXX, entitled "Wireless Channel Estimation", and

U.S. Patent Application Serial No. 10/XXX,XXX, entitled
Repetition Coding For A Wireless System, all filed on
September 17, 2003 by Atheros Communications, Inc. and
incorporated by reference herein, describe aspects of XR
signal detection as well as packet detection mechanisms.
U.S. Patent Application Serial No. 09/849,595, entitled,
"Self-Correlation Detection In Automatic Gain Calibration",
filed on May 4, 2001 and also incorporated by reference
herein, describes embodiments of power measurement block
140, packet detection block 160, as well as the packet
detection mechanisms forming part of identifiers 127-129.

Modulation Identification In Demodulation Mode

[0056]   In general, voting block 130 chooses the highest
probability modulation for decoding the detected packet
based on the analysis of the received signal in light of
different identification (ID) values. Specifically, one or
more of identifiers 127, 128, and 129 can provide an ID
value to voting block 130 based on comparing the output
signal of its corresponding filter to unique
characteristics associated with its modulation type. The
ID value indicates the likelihood that the filtered signal
is of a certain modulation type.

[0057]   In one simple embodiment, voting block 130 can
determine the highest of the three ID values, thereby
designating the most probable modulation type. In other
embodiments of the invention described in further detail
below, voting block 130 can use the ID values in various
algorithms to determine the most probable modulation type.
Voting block 130 can advantageously provide its output to
CCK decoder 114 and OFDM/XR decoder 113, thereby ensuring
that one of the two decoders can be used to properly decode

the received signal and the other decoder can be
deactivated.   In one embodiment, voting block 130 can
further provide its output to gain control 112, thereby
allowing additional fine adjustment of the gains of RF
amplifier 103, IF amplifier 105, and baseband amplifiers
108 (Figure 1A) based on the modulation of the packet.

[0058]   Note that to effectively detect and identify the
modulation of the received signals, it would be desirable
to have a base sampling rate of 20 MHz for OFDM/XR signals
and 11 MHz for CCK signals.   Because the components of
receiver 100 cannot be simultaneously run at both
frequencies, only one of the two base sampling rates is
used.   Therefore, in one embodiment of a WLAN receiver
operating in conformance with the 802.11g standard,
processing block 111 can be run at 44 MHz.   Thus, if voting
block 130 determines that an OFDM or XR packet has been
received, then interpolator 124 can be used to reduce 44
MHz to 40 MHz.

Signal Modulation Identification (802.11g, XR Disabled)

[0059]   After receiver 100 (XR capability disabled)
detects a signal, makes any appropriate gain adjustment to
its variable amplifiers, and asserts the agc_done signal,
OFDM identifier 127, CCK identifier 128, and voting block
130 can determine the modulation type of the signal.   In
one embodiment, this identification is dependent on the
strength of the detected signal.

[0060]   Figure 4A illustrates an exemplary technique 400
for determining the modulation type of the detected signal.
In step 401, a determination can be made whether the
detected signal is strong or weak.   In processing block 111
(Figure 1B), power measurement block 140 can make this

determination.   If the detected signal is a weak signal,
then the raw RSSI of the detected signal can be compared to
a threshold RSSI in step 402.

[0061]   This threshold RSSI can be used to distinguish
truly weak signals from intermediate strength signals.
Specifically, under certain circumstances, an intermediate
strength OFDM signal can initially trigger a CCK
identification instead of an OFDM identification.   Thus, a
threshold RSSI can be used to increase the probability that
the correct modulation is identified.   Note that this
threshold value can be adjusted based on user feedback.
For example, if an incorrect modulation type is being
consistently identified, then the threshold value can be
adjusted accordingly.

[0062]   If the raw RSSI of the signal is less than the
threshold RSSI (i.e. the detected signal is a truly weak
signal), then the modulation type indicated during the
search mode can be used in step 403.   Note that during the
search mode, after the first of identifiers 127-129 exceeds
its threshold value in weak signal detection, packet
detection block 160 notes the identified modulation type
and stops the search mode.   In one embodiment, packet
detection block 160 (Figure 1B) can provide its modulation
identification to voting block 130 during search mode 310.
Moreover, power measurement block 140 can compute the
values in steps 401 and 402 during search mode 310.   In
this manner, identification of the most probable modulation
type for a weak signal can occur immediately after the
agc_done signal is asserted (step 303).   In other
embodiments, packet detection block 160 (Figure 1B) can
provide its modulation identification to voting block 130
during demodulation mode 320.   Moreover, power measurement

block 140 can compute the values in steps 401 and 402
during demodulation mode 320.

[0063]   If packet detection block 160 identifies a weak
signal OFDM packet, then voting block 130 can allow OFDM
decoder block 113 to continue decoding the packet and
advantageously deactivate CCK decoder block 114 (as well as
other CCK-related components as discussed in reference to
Figure 1C). Similarly, if packet detection block 160
identifies a weak signal CCK packet, then voting block 130
can allow CCK decoder block 114 to continue decoding the
packet and advantageously deactivate OFDM decoder block 113
(and other OFDM-related components as discussed in
reference to Figure 1D).

[0064]   In one embodiment, if the raw RSSI of the signal
is greater than a threshold RSSI (i.e. rssi >
weak_vote_thr), then the modulation-specific RSSIs can be
computed and voted on in step 404. The modulation-specific
RSSIs generated by OFDM identifier 127 and CCK identifier
128 are referenced herein as a cyclic_rssi and a
barker_rssi, respectively. Note that an RSSI is typically
based on raw power, i.e. un-normalized (sum of squares)
power. Because OFDM identifier 127 and CCK identifier 128
might be less than perfect correlators, the power can be
accordingly adjusted for each identifier. In a typical
embodiment, the power is decreased, i.e. the RSSIs of OFDM
correlator 127 and CCK correlator 128 are decreased by the
effect of the noise to be less than the sum of squares
power.

[0065]   Note that the modulation-specific RSSI
corresponding to the transmitted modulation type would
ideally be comparable in value to the raw RSSI, whereas any
modulation-specific RSSI not corresponding to the

transmitted modulation type would be significantly lower. For example, in one embodiment, the difference in power between the raw RSSI and the modulation-specific RSSI for the correct modulation type can be between 1-4 dB, whereas the modulation-specific RSSI for the incorrect modulation type should be even lower.

[0066]   To compute the modulation-specific RSSI, an identifier can first perform a noise floor measurement, i.e. a measurement (calibrated or uncalibrated) based on the thermal noise on the medium without a signal. In one embodiment, the noise floor can be computed by subtracting the amount of total variable gain in all amplifiers being used from the measured noise power at ADCs 110 (both values being in dBs). This measurement is described in U.S. Patent Application Serial No. 10/254,151, entitled "Method And System for Noise Floor Calibration And Receive Signal Strength Detection", filed on September 25, 2002 by Atheros Communications, Inc., and incorporated by reference herein.

[0067]   At this point, as shown in the following equation, the RSSI can be computed by subtracting the noise floor as well as the amount of variable gain from the squared magnitude of the correlation after being converted to dBs (i.e. log domain) in a look-up table.

$$\text{Modulation\_specific\_RSSI} = (\text{Log}_{10}(\text{Correlator\_output}^2) - \text{variable\_gain}) - \text{noisefloor}$$

[0068]   Thus, for a desired modulation type, the computed modulation-specific RSSI is similar to a signal to noise ratio (SNR), but one that is based on the correlation of the modulation type (i.e. self-correlation for the OFDM identifier and cross-correlation for the CCK identifier).

[0069]   After computing the modulation-specific RSSIs in step 404, voting block 130, which receives the power output

22

from OFDM identifier 127 and CCK identifier 128, can
normalize these RSSIs by the variable gain and then
implement an appropriate voting technique in step 405. In
one embodiment, voting block 130 can implement a voting
technique that determines whether the cyclic_rssi added to
a bias value (referenced generically herein as bias_value)
is greater than the barker_rssi. The following equation
can represent such a voting technique.

cyc_gt_barker = (cyc_rssi + ofdm_cck_bias_value) >
barker_rssi

[0070]   In one embodiment, the bias value can
advantageously adjust the probability of choosing different
modulated signals in the receiver. Note that this bias
value can be computed before signal detection, during
search mode 310, or during demodulation mode 320.

[0071]   In one embodiment, this probability adjustment
can take into account different signal environments. For
example, if strong multipath is present in the environment,
then the barker_rssi degrades more rapidly than the
cyclic_rssi. That is, a self-correlation is logically much
more immune to multipath effects than a cross-correlation.

[0072]   Thus, in one embodiment, a default
ofdm_cck_bias_value can be set negative. The
ofdm_cck_bias_value can be increased relative to the
default ofdm_cck_bias_value to make OFDM more likely and
decreased to make CCK more likely. In one embodiment, the
default ofdm_cck_bias_value can be set to -3.

[0073]   If cyc_gt_barker is true, then voting block 130
identifies the signal as an OFDM signal, allows OFDM
decoder block 113 to continue decoding the packet, and
advantageously deactivates CCK decoder block 114 (as well
as other CCK-related components as discussed in reference

to Figure 1C). If cyc_gt_barker is false, then voting
block 130 identifies the signal as a CCK signal, allows CCK
decoder block 114 to continue decoding the packet, and
advantageously deactivates OFDM decoder block 113 (and
other OFDM-related components as discussed in reference to
Figure 1D).

Signal Modulation Identification (802.g, XR Enabled)

[0074]   Some wireless devices can send and receive
packets from exceptionally long distances using a
modulation called extend range (XR)(proprietary to Atheros
Communications, Inc.). In one embodiment, WLAN devices
must be XR-enabled to detect and identify XR signals. In
simple terms, the XR signal includes distributing repeated
values of an 802.11a (OFDM) signal across multiple sub-
carriers, thereby decreasing its data rate as well as
decreasing the received signal to noise ratio (SNR)
required to decode the XR signal.

[0075]   XR-enabled clients cannot send unsolicited data
to the access point. Instead, an access point typically
polls these clients to send data. The period between
pollings, particularly for XR-enabled clients that are
already pushing the boundary of transmission, can be too
long.

[0076]   Therefore, in one embodiment, to reduce the
period between pollings, an XR-enabled client can "chirp"
to an access point. In one embodiment, a chirp can include
an XR header with no accompanying data. In another
embodiment, a chirp can include a pair of XR headers
concatenated together, i.e. a double chirp, again with no
accompanying data.

[0077]   Thus, the single or double chirp indicates that the XR-enabled client has data to send to the access point. The single or double chirp can further indicate what type of information will be transmitted. After receiving a chirp/double chirp, an access point can respond with another chip, thereby indicating to other XR-enabled clients that they cannot chirp until a predetermined time has lapsed. At this point, the access point will schedule a polling of the first chirp XR-enabled client as soon as possible.

[0078]   Of importance, the access point must also be XR-enabled to communicate with similarly enabled clients. In one embodiment, the MAC of the access point can decide which type of signal that processing block 111 should look for by setting its XR mode bits, called an xr_chirp_mode. Table 1 indicates the supported packet types in 802.11a mode when extended range is enabled.

TABLE 1: Packet Types In 802.11a Mode, XR Enabled

XR_chirp_mode	Possible Packet Types
00	OFDM packet or XR packet
01	Single Chirp
10	OFDM packet or Double Chirp
11	Invalid

[0079]   Table 2 indicates the supported packet types in 802.11g mode when extended range is enabled. Note that in one embodiment, when the WLAN device operates in the 802.11b mode, extended range modulation is disabled.

TABLE 2: Packet Types In 802.11g Mode Including XR
Modulation

Rx_chirp_mode	Possible Packet Types
00	OFDM packet or XR packet
01	Single Chirp
10	OFDM packet, CCK packet, or Double Chirp
11	Invalid

[0080]   As described above, the XR signal includes unique
characteristics in its header, thereby facilitating
identification of a weak XR signal using a combined self-
and cross-correlation. Specifically, weak signal
identification of XR signals can be performed using the 15
symbols (i.e. the medium sequences) in the XR preamble. As
noted previously, these medium sequences are combined with
a secondary PN codes, such that each medium sequence has a
predetermined sign (i.e. +/-). Thus, XR signal
identification can be performed by cross-correlating the
detected signal with a single medium sequence, then self-
correlating this output over a gap of the duration of a
medium sequence. Because of the long duration of the XR
preamble and the complexity of this cross- and self-
correlation, XR identifier 129 could take between 24-48 µs
for identification of a weak XR signal. In one embodiment,
because such time constraints, the XR modulation type
identification in the demodulation mode 320 can be limited
to a cross-correlation of one medium sequence without
sacrificing significant accuracy.

[0081]   To implement step 405 (Figure 4) when receiver
100 is in the "00" XR_chirp_mode or the "00" Rx_chirp_mode,

processing block 111 can determine whether the signal is
OFDM or extended range by comparing the cyclic_rssi and the
XR RSSI. Specifically, voting block 130 can implement a
voting technique that determines whether an OFDM RSSI added
to a bias RSSI is greater than an XR RSSI. The voting
technique can be represented by the following equation:
cyc_gt_xr = (cyc_rssi + ofdm_xr_bias_value >
extended_range_rssi).

[0082]   Note that the bias value ofdm_xr_bias_value
serves substantially the same purpose as the
ofdm_cck_bias_value. That is, the ofdm_xr_bias_value can
advantageously account for the probability associated with
encountering OFDM and XR signals in different environments.
The bias value can be increased to make OFDM identification
more likely or decreased to make XR identification more
likely. In one embodiment, the ofdm_xr_bias_value can be
based on 64 samples, which can be a subset of the preamble,
thereby advantageously reducing the time to identify the
signal.

[0083]   If cyc_gt_xr is true, then the detected signal is
identified as an OFDM signal. Otherwise, the signal is
identified as an XR signal.

[0084]   To implement step 405 (Figure 4) when receiver
100 is in the "01" XR_chirp_mode or the "01" Rx_chirp_mode,
no voting is necessary and receiver 100 is merely notified
that only detection of chirps is needed. Similarly, when
receiver 100 is in the "10" XR_chirp_mode, no voting is
necessary. In this case, receiver 100 starts the decoding
of that signal in parallel paths assuming both OFDM
modulation and XR modulation. If an XR double chirp is
detected at a later point in time, then the process aborts
the OFDM decoding and proceeds with an XR transmission.

[0085]   In contrast, when receiver 100 is in the "10" Rx_chirp_mode (i.e. the packet type could be OFDM, CCK, or double chirp, as shown in Table 2), distinguishing between a CCK and an XR signal in heavy multipath can pose significant challenges. Specifically, in contrast to a pure self-correlation found in an OFDM signal (and thus not degrading under multipath conditions), both CCK and XR signals (which include cross-correlation properties) can degrade rapidly under multipath conditions.

[0086]   Therefore, in one embodiment, the voting technique can include comparing the OFDM RSSI and the CCK RSSI and then, if necessary, comparing the OFDM RSSI and the XR RSSI. Figure 4A illustrates an exemplary implementation of step 405 to provide such comparisons. For example, step 411 can determine whether the OFDM RSSI added to a bias value is greater than the CCK RSSI (i.e. cyc_gt_barker). The following equation describes this voting technique:

cyc_gt_barker = (cyc_rssi + ofdm_cck_bias_value) > barker_rssi

[0087]   If cyc_gt_barker is not true, then the voting block identifies the signal as a CCK signal and starts the decoding of that signal in parallel paths assuming both CCK modulation and XR modulation in step 412. At this point, if an XR double chirp is detected, then the process aborts the CCK decoding and proceeds with an XR decoding.

[0088]   If cyc_gt_barker is true, then step 413 determines whether the OFDM RSSI added to a bias value is greater than the XR RSSI (i.e. cyc_gt_xr). The following equation describes this voting technique:

cyc_gt_xr = (cyc_rssi + ofdm_xr_bias_value > extended_range_rssi).

[0089]   If cyc_gt_xr is not true, then the voting block
identifies the signal as an XR signal in step 414 and
begins a decoding of the signal based on XR modulation.   If
cyc_gt_xr is true, then the voting block identifies the
signal as an OFDM signal and begins a decoding of the
signal based on OFDM modulation in step 415.

Other Embodiments

[0090]   Although illustrative embodiments have been
described in detail herein with reference to the
accompanying figures, it is to be understood that the
invention is not limited to those precise embodiments.
They are not intended to be exhaustive or to limit the
invention to the precise forms disclosed.   As such, many
modifications and variations will be apparent to
practitioners skilled in this art.

[0091]   For example, as described above, a bias value can
be used based on a specific environment and a signal's
response in that environment.   In another embodiment, the
bias value can reflect a user's bias in wanting to identify
certain type of signals.   For example, a user may
prioritize receiving OFDM signals and not CCK.   In that
case, the bias value can be used to increase the
probability of identifying OFDM signals at the expense of
identifying CCK signals.

[0092]   In one embodiment, a system for determining a
modulation of a received signal in a receiver is also
provided.   The system can include means for providing an
identification value for one or more potential types of
modulation based on the received signal.   The system can
further include means for determining the most probable
modulation based on such identification values.   Other

components of the system can provide other functions described in reference to Figures 1B, 3, 4A, and 4B.

[0093]   In another embodiment including an appropriately fast microprocessor, a computer software program for determining a modulation of a received signal can also be provided. The program can include code for providing an identification value for one or more potential types of modulation based on the received signal. The program can further include code for determining the most probable modulation based on such identification values. Other code of the program can implement other functions described in reference to Figures 1B, 3, 4A, and 4B.

[0094]   Note that in one embodiment, CCK identifier 128 can be implemented as part of CCK decoder block 114. Similarly, OFDM identifier and XR identifier can be implemented as part of OFDM/XR decoder block 113. In another embodiment, gain control 112 and packet detection block 160 can be integrally implemented. In yet another embodiment, voting block 130 and packet detection block 160 can be integrally implemented.

[0095]   In another embodiment, an intermediate signal detection can trigger CCK identifier 128 to analyze and generate results regarding multiple portions of the received signal, thereby correcting for an early misidentification. For example, CCK identifier 128 can calculate the coherent sum of two consecutive normalized Barker correlations, wherein if the sum exceeds a predetermined threshold value (i.e. weak_sig_thr_cck), then CCK identifer 128 can send its output to voting block 130. Otherwise, CCK identifier 128 provides no output to voting block 130. In this manner, CCK identifier 128 can

advantageously prevent erroneous detection of barker
signals.

[0096]   Accordingly, it is intended that the scope of the
invention be defined by the following Claims and their
equivalents.